## Yuasa Technical Data Sheet

#### Yuasa RE7-12LFR Industrial VRLA Battery

Specifications

Nominal voltage (V)

20-hr rate Capacity to 10.5V at 20°C (Ah)

10-hr rate Capacity to 10.8V at 20°C (Ah)

6.2

**Dimensions** 

 $\begin{array}{lll} \text{Length (mm)} & & 151 \ (\pm 1) \\ \text{Width (mm)} & & 65 \ (\pm 1) \\ \text{Height (mm)} & & 94 \ (\pm 1) \\ \text{Height over terminals (mm)} & & 97,5 \ (\pm 1) \\ \text{Mass (kg)} & & 2.75 \\ \end{array}$ 

**Terminal Type** 

FASTON - Quickfit / release (IST where stated) 6.35

**Operating Temperature Range** 

Storage (in fully charged condition)  $-15^{\circ}\text{C}$  to  $+45^{\circ}\text{C}$  Charge  $-15^{\circ}\text{C}$  to  $+45^{\circ}\text{C}$  Discharge  $-15^{\circ}\text{C}$  to  $+45^{\circ}\text{C}$ 

Storage

Capacity loss per month at 20°C (% approx.)

**Case Material** 

Standard ABS (UL94:V0)

**Charge Voltage** 

Float charge voltage at 20°C (V)/Block 13.65 ( $\pm$ 1%) Float charge voltage at 20°C (V)/Cell 2.275 ( $\pm$ 1%)

Float Chg voltage tmp correction factor from std -3

20°C (mV)

Cyclic (or Boost) charge Voltage at 20°C (V)/Block 14.5 (±3%) Cyclic (or Boost) charge Voltage at 20°C (V)/Cell 2.42 (±3%) Cyclic Chg voltage tmp correction factor from std -4

20°C (mV)

**Charge Current** 

Float charge current limit (A) No limit Cyclic (or Boost) charge current limit (A) 1.75

**Maximum Discharge Current** 

1 second (A) 105 1 minute (A) 42

**Impedance** 

Measured at 1 kHz ( $m\Omega$ ) 35


**Design Life & Approvals** 

EUROBAT Classification: General Purpose 6 to 9 Yuasa design life at 20°C (yrs) up to 10





#### Layout



### **3rd Party Certifications**

ISO9001 - Quality Management Systems UNDERWRITERS LABORATORIES Inc.





# Safety

#### Installation

Can be installed and operated in any orientation except permanently inverted.

#### Handles

Batteries must not be suspended by their handles (where fitted).

#### **Vent valves**

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

#### Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

#### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.







